Harmonic balance approach to limit cycles for non-linear jerk equations

H. P. W. Gottlieb

School of Science, Griffith University, Nathan, Queensland 4111, Australia

8 December 2005

Running Title: LIMIT CYCLES FOR JERK EQUATIONS

Number of Pages: 20,
including 4 Figures
and 2 Tables.

Abstract

The method of harmonic balance (HB) is employed to estimate the attributes of limit cycles of some nonlinear third-order (jerk) differential equations which are parity-invariant but not time-reversal-invariant. Two examples with cubic nonlinearities show that the HB method can give good values for the frequency and both the velocity and displacement amplitudes of a period one limit cycle.

Keywords: Limit cycles; harmonic balance; jerk; nonlinear

E-mail address: H.Gottlieb@griffith.edu.au

1. Introduction

In a previous paper [1], the author applied the method of Harmonic Balance (HB) (see e.g. [2] for second-order ordinary differential equations (o.d.es)) to some non-linear jerk equations, which are o.d.es expressing the third time-derivative of displacement x in terms of x and its first and second derivatives. Several examples exhibiting oscillations were analysed and results were compared with numerical solutions, exhibiting good agreement over a range of parameter values. The method is limited by its nature to zero initial acceleration (when started from zero initial displacement), but was rather successful for that situation. The terms in the jerk equations as considered in [1], as well as being parity-invariant, were also time-reversal invariant. For such equations, having ordinary periodic solutions (a centre), the initial velocity amplitude may be assigned and then it maintains that value subsequently.

If the restriction to time-reversal invariance is dropped, there results the possibility of obtaining limit cycles (LCs). As in the case of second-order, i.e. acceleration, differential equations ([2, pp. 154-155]), the HB method may be able to detect limit cycles: it then involves the coefficients of both cosine and sine terms, and leads to two simultaneous approximate equations for both the angular frequency Ω and an amplitude. The study of such limit cycles for nonlinear jerk equations is the subject of this paper. The results of some numerical experiments are reported and compared with the HB estimates.

It should be stressed that this paper deals with isolated limit cycles, i.e. of period one (single loop), away from any possible chaotic regions. Third (and higher) dimension systems commonly have a series of period-doubling limit cycles that involve multiple loops which successively split further towards chaos as a parameter is varied (c.f. e.g. [3, p.83 and p.94]). Evidently an HB approach as outlined above would not describe such cascading situations.

In the present case, the initial velocity amplitude does not persist (unless evolution happens to start exactly on a limit cycle): for limit cycles, path parameters cannot be set a priori. Some questions arise for these third-order oscillators. Does HB give a good estimate of the actual limit cycle period? Does the HB approximation B^{HB}

give a good estimate for the velocity amplitude B on the limit cycle, and does the corresponding A^{HB} give a good estimate of its displacement amplitude A ? These questions will be treated below.

2. Harmonic balance and limit cycles

The harmonic balance method for jerk equations [1] sets

$$x = \frac{B}{\Omega} \sin \Omega t \equiv A \sin \Omega t \quad (2.1)$$

so

$$\dot{x} = B \cos \Omega t, \quad (2.2a)$$

$$\ddot{x} = -\Omega B \sin \Omega t \equiv C \sin \Omega t, \quad (2.2b)$$

$$\ddot{\ddot{x}} = -\Omega^2 B \cos \Omega t. \quad (2.2c)$$

A number of linear and nonlinear terms may contribute to the jerk function

$$\ddot{\ddot{x}} = j(x, \dot{x}, \ddot{x}). \quad (2.3)$$

Consideration here is limited to odd-parity terms in j , suitable for the conventional approach via harmonic balance, and to polynomial terms not higher than third order. There are four categories of terms: linear (L) or non-linear (NL), odd (OT) or even (ET) under time reversal, $\ddot{\ddot{x}}$ itself being (L, OT):

L, OT: $\dot{x}$;

L, ET: $x, \ddot{x}$;

NL, OT: $\dot{x}^3, x^2 \dot{x}, x \dot{x} \ddot{x}, \dot{x} \ddot{x}^2$;

NL, ET: $x^3, x^2 \ddot{x}, x \dot{x}^2, x \ddot{x}^2, \ddot{x}^3, \dot{x}^2 \ddot{x}$.

The OT terms alone were dealt with in the previous paper on periodic (centre) solutions [1]. For a limit cycle, there must be two relations. One must come from “balancing” the jerk term $\ddot{x}$ (L, OT) with at least one term from L, OT and/or NL, OT. Another relation must come from the ET terms, at least two of which must therefore be present. The HB results may then be compared with results obtained by numerical integration of the jerk d.e.s. In all cases, the initial conditions are taken as

$$x(0) = 0 = \ddot{x}(0) \quad , \quad (2.4)$$

following from (2.1) and (2.2b), as discussed at length in [1].

3. Jerk equation involving Euclidean norm nonlinearity

Some time ago, Mulholland [4] considered the non-linear oscillations of a third-order (i.e. jerk) equation whose non-linearity depended on the Euclidean norm of the associated phase space (sum of squares of dynamical quantities), and analysed the limit cycle solution. His equation may be written in the form

$$\ddot{x} = -x - (1-\eta)(\dot{x} + \ddot{x}) - \eta (\dot{x} + \ddot{x}) (x^2 + \dot{x}^2 + \ddot{x}^2) \quad (3.1)$$

where η is a positive parameter. This has as nonlinearities three terms from the class (NL, OT) and three terms from (NL, ET) as categorized in Section 2 above.

The origin of the three-dimensional phase space is the sole equilibrium point, and the corresponding linearized equation is

$$\ddot{x} + (1-\eta)\ddot{x} + (1-\eta)\dot{x} + x = 0 \quad . \quad (3.2)$$

The roots of the characteristic equation (c.f. Appendix) corresponding to (3.2) are explicitly given (c.f. [4]) by $\Lambda_1 = -1$, $\Lambda_{2,3} = (1/2) [\eta \pm \sqrt{(\eta^2 - 4)}]$, so the real parts of the second and third roots are positive for any positive value of η , so the origin is unstable. We may note that, in the notation of the Appendix with a,b,c as the

coefficients respectively of the second, first and zeroth order derivatives in (3.2), $ab = (1-\eta)^2$ and $c=1$. The necessary and sufficient condition for stability of (3.2), namely $a, b, c > 0$ and $c < ab$ (see equation (A.2)) is therefore never satisfied, confirming the aforementioned instability. As mentioned in [4], this is necessary for the existence of a nearby limit cycle, i.e. one encircling the origin.

We are here interested in whether the Harmonic Balance (HB) procedure can give good estimates of the limit cycle parameters compared with the "exact" values found by numerical integration. The HB procedure of Section 2 utilises identities to re-express powers and products of trigonometric functions. Equating first the coefficients of the $\cos(\Omega t)$ term yields

$$B^2 = \frac{4}{\eta} \frac{\Omega^2(\Omega^2 + \eta - 1)}{\Omega^4 + 3\Omega^2 + 1} . \quad (3.3)$$

Secondly, the coefficients of the $\sin(\Omega t)$ term yield

$$B^2 = \frac{4}{\eta} \frac{1 - (1-\eta)\Omega^2}{3\Omega^4 + \Omega^2 + 3} . \quad (3.4)$$

Together, these give a quartic equation in Ω^2 :

$$3(\Omega^2)^4 + (2\eta-1)(\Omega^2)^3 + (4-2\eta)(\Omega^2)^2 + (2\eta-5)(\Omega^2) - 1 = 0 . \quad (3.5)$$

For given value of parameter η , this can be solved numerically for the positive solution for Ω^2 to give the approximate angular frequency Ω^{HB} and hence the harmonic balance period value

$$T^{\text{HB}} \equiv 2\pi/\Omega^{\text{HB}} . \quad (3.6)$$

Then the approximate velocity amplitude B^{HB} can be found by substitution from either above equation (3.3,4) for B^2 ; and then the approximate displacement amplitude is given by (2.1) as

$$A^{HB} = B^{HB}/\Omega^{HB} . \quad (3.7)$$

The harmonic balance approximate displacement is then given in terms of the above by

$$x^{HB} = \left(B^{HB} / \Omega^{HB} \right) \sin(\Omega^{HB} t) . \quad (3.8)$$

If $\eta=0$, then $\Omega=1$ is the solution, and $x = A \sin t$ with A arbitrary is the exact solution (for $x(0) = 0 = \ddot{x}(0)$) of the resulting d.e., which is linear. For η small, make a perturbation: $\Omega = 1+\Delta$. The result, to first order in η , assuming Δ is also small, is found from (3.5) to be $\Delta = - (1/12) \eta \approx - 0.08333 \eta$. This may be compared with Mulholland, who also obtained $\Delta = - (1/12) \eta$ by an averaging method; he also obtained $\Delta = - 0.084\eta$ by a perturbation method on the d.e.. The approximate angular frequency, to first order (FO) in η , is therefore $\Omega_{FO\eta}^{HB} = 1 - \eta/12$. Then the approximate period, to first order in η , is

$$T_{FO\eta}^{HB} = 2\pi[1 + (\eta/12)] . \quad (3.9)$$

The harmonic balance (HB) values (3.6), (3.3,4), (3.7), obtained via (3.5), can be compared with the exact (EX) values for period, velocity amplitude and displacement amplitude obtained by numerically integrating the non-linear o.d.e. (3.1) (using ODE Workbench [5]) and letting the system settle onto its limit cycle (LC) in the $x, \dot{x}$ plane before determining T , B and A . For this paper, the stability of the limit cycle was confirmed numerically, in that the values remained unchanged over many cycles, after several hundred initial circuits. As a check, results for the $\ddot{x}, \dot{x}$ phase plane (which has the same initial conditions) were also computed, and found to agree.

Some results for several values of the parameter η are displayed in Table 1. The results for periods are also compared with the harmonic balance first order (in η) (HB,FO η) expansion result (3.9) for small η . In addition, the value $\ddot{x}_{LC0}$ of the second derivative $\ddot{x}$ on the computed limit cycle when $x=0$ was noted, for comparison with the harmonic balance value of zero corresponding to equations (2.2b) and (2.1). It can be seen that the HB values are in good agreement with the

exact values, to within just a few percent. The results improve as the value of $\ddot{x}_{LC0}$ more nearly approaches zero, which is consistent with the conditions discussed for the HB method in this application. For this d.e., this corresponds to decreasing value of the parameter η .

4. A modified simple dissipative jerk equation

Consider the following jerk equation, which is a modification of a simple dissipative jerk equation due to Malsoma [6] extended by the inclusion of a term linear in velocity:

$$\ddot{x} = -\lambda \ddot{x} + x \dot{x}^2 - \gamma \dot{x} - x ; \quad \lambda > 0 , \gamma > 0 . \quad (4.1)$$

There are overall two terms of type (L,OT) of Section 2, and two of type (L,ET); the nonlinearity in (4.1) is of the type (NL, ET).

The HB approach for this d.e. as described in Section 2 leads to

$$\Omega^{HB} = \sqrt{\gamma} \quad ; \quad T^{HB} = 2\pi/\sqrt{\gamma} , \quad (4.2)$$

$$B^{HB} = 2\sqrt{1-\lambda\gamma} \quad (4.3)$$

with

$$A^{HB} \equiv B^{HB} / \Omega^{HB} = 2\sqrt{1-\lambda\gamma} / \sqrt{\gamma} , \quad (4.4)$$

and the approximate acceleration amplitude is given by

$$C^{HB} \equiv -B^{HB} \Omega^{HB} = -2\sqrt{1-\lambda\gamma} \sqrt{\gamma} . \quad (4.5)$$

Then the harmonic balance approximate displacement is given explicitly by

$$x^{HB} = 2 \left[\sqrt{1-\lambda\gamma} / \sqrt{\gamma} \right] \sin(\sqrt{\gamma} t) . \quad (4.6)$$

(Unlike the complexity of the example of Section 3 above, here the formulae for Ω^{HB} and B^{HB} , etc., are simple and explicit.)

For convenience, the parameters λ and γ are here chosen such that

$$\lambda\gamma = 3/4 \quad (4.7a)$$

so

$$B^{HB} = 1 ; \quad A^{HB} = 1/\sqrt{\gamma} , \quad T^{HB} = 2\pi/\sqrt{\gamma} , \quad C^{HB} = -\sqrt{\gamma} . \quad (4.7b)$$

The characteristic equation of the linearized equation corresponding to (4.1), with (4.7a), is

$$\Lambda^3 + \lambda \Lambda^2 + [3/(4\lambda)] \Lambda + 1 = 0 . \quad (4.8)$$

In (4.8) all coefficients are positive and, in the notation of the Appendix for the coefficients of a cubic, $c = 1 > 3/4 = ab$. Thus by (A.2), the equilibrium point at the origin is unstable. This suggests the possibility of a nearby limit cycle, encircling the origin. (Note that, for the cubic characteristic equation resulting from the linearized equation corresponding to (4.1) with general coefficients, instability of the origin requires $ab < c$, i.e. $\lambda\gamma < 1$ (satisfied by (4.7a). This is consistent with requiring (4.3) to be real, so that HB approximations exist.)

Table 2 compares Harmonic Balance values with numerically determined exact values (obtained using the software [5]), for several parameter combinations satisfying (4.7a). It can be seen that the harmonic balance approximations give good estimates of the limit cycle (LC) values. As expected, the accuracy again improves as $\ddot{x}_{LC0}$ gets closer to zero, which in this case corresponds to decreasing λ , i.e. here, increasing γ .

It may be mentioned that when the $\ddot{x}, \dot{x}$ phase plane was investigated, the "B" value of the limit cycle, i.e. $\dot{x}$ axis intercept when $\ddot{x}$ is zero, was slightly different from the B value found in the usual $x, \dot{x}$ phase plane. The difference was less than 0.3% for the first parameter set in Table 2, and much less for the other two cases. This is due to the fact that the orbit actually moves in the three-dimensional phase space, so there would be slightly different projections onto the $\dot{x}$ axis in the two planes. Such details lie beyond the precision of the HB approach.

Figures 1, 2, 3, 4 show some phase plane trajectories for the nonlinear jerk equation (4.1) for the case (see Table 2) $\gamma=4$, $\lambda=3/16=0.1875$. Figure 1, for $\dot{x} \equiv y$ vs x with $\dot{x}(0)=0.5$ (and $x(0)=0=\ddot{x}(0)$), shows the spiralling out from the unstable origin to the stable limit cycle. (For a choice such as $\dot{x}(0)=0.01$, the path uncoils from much nearer the origin, much more densely.) Figures 2, 3, 4 start with $\dot{x}(0)=B^{HB}=1$ (and $x(0)=0=\ddot{x}(0)$), for the phase planes indicated, where $y=\dot{x}$, $z=\ddot{x}$. The pictures for the x,y and z,y planes (which have the same initial conditions) look qualitatively similar, although with different oblateness. It should be noted that $B^{HB}=1$, $A^{HB}=0.5$ and $C^{HB}=-2$ here, and these B and A harmonic balance (HB) values are very close to their limit cycle (LC) values as tabulated in the second row of Table 2. Furthermore, C^{HB} is also very close to the limit cycle value which was found by computation (see Figure 3) to be $C^{LC}=-2.000253$. In Figures 2 and 3, the trajectories spiral inwards towards the limit cycle, as indicated by the final value designators. The picture in Figure 4 (in which initial transients have been omitted) for the x,z plane is quite different, and shows the slight departure from $z \propto -x$ which would pertain if the harmonic balance equations (2.1), (2.2b) were exact. The value of $\ddot{x}|_{x=0}$ is evidently not exactly zero, but for these parameters is nevertheless small on the limit cycle, which is why the harmonic balance approximation does give good results here.

5. Conclusion

For limit cycles, the amplitudes are determined by the dynamical system and are not assigned as initial conditions, unlike the case of ordinary periodic solutions

(centres). In particular, the acceleration on the limit cycle might not be zero when the displacement is zero. Thus Harmonic Balance for limit cycles of jerk equations might be expected to be less successful than for centres as studied in reference [1].

Nevertheless, the above examples show that, for a range of equation coefficients, the HB method can give good results. This is borne out by the two jerk equations having very different cubic nonlinearity terms.

The method will only be appropriate for jerk equations with (at least) one term in the jerk expression of the type OT (odd under time-reversal) and (at least) two terms of the type ET (even under time reversal), but this represents a sufficiently large class of equations to be of importance.

Appendix

A general cubic equation may be written in the form

$$f(\Lambda) \equiv \Lambda^3 + a\Lambda^2 + b\Lambda + c = 0 ; \quad a, b, c \text{ real.} \quad (\text{A.1})$$

One approach to examining the stability of a third-order linearized system whose characteristic equation is a cubic equation such as (A.1) is to note that for stability it is necessary that none of the roots has a positive real part. For all roots real and negative, this corresponds to a node; for one root real and negative and the other two complex conjugate with negative real part, to a spiral node (see e.g. [3, pp.81-82]). This requires that all three coefficients in (A.1) be positive (see [7, pp. 242-4]). Further analysis as in [7] yields the necessary and sufficient conditions for stability associated with (A.1) as

$$a > 0, \quad b > 0, \quad c > 0; \quad c < ab. \quad (\text{A.2})$$

References

- [1] H.P.W. Gottlieb, Harmonic balance approach to periodic solutions of non-linear jerk equations, *Journal of Sound and Vibration* 271 (2004) 671-683.
- [2] R.E. Mickens, *Oscillations in Planar Dynamical Systems*, World Scientific, Singapore, 1996.
- [3] J.C. Sprott, *Chaos and Time-Series Analysis*, Oxford University Press, Oxford, 2003.
- [4] R.J. Mulholland, Non-linear oscillations of a third-order differential equation, *International Journal of Non-Linear Mechanics* 6 (1971) 279-294.
- [5] J.M. Aguirregabiria, *ODE Workbench (PC Version 1.5)*, American Institute of Physics, New York, 1994.
- [6] J.-M. Malasoma, What is the simplest dissipative chaotic jerk equation which is parity invariant?, *Physics Letters A* 264 (2000) 383-389.
- [7] T. v. Karman & M.A. Biot, *Mathematical Methods in Engineering*, McGraw-Hill, New York, 1940.

Figure Captions.

Figure 1. Jerk equation (4.1), $y = \dot{x}$: parameters $\gamma=4, \lambda=3/16$; $\dot{x}(0) = 0.5$.

Figure 2. Jerk equation (4.1), $y = \dot{x}$: $\gamma=4, \lambda=3/16$; $\dot{x}(0) = 1$.

Figure 3. Jerk equation (4.1), $y = \dot{x}, z = \ddot{x}$: parameters $\gamma=4, \lambda=3/16$; $\dot{x}(0) = 1$.

Figure 4. Jerk equation (4.1), $z = \ddot{x}$: parameters $\gamma=4, \lambda=3/16$; $\dot{x}(0) = 1$. (Transients up to $\sim 100T$ omitted.)

Table captions.

Table 1

Period T , velocity amplitude B , and displacement amplitude A , for the Mulholland equation (3.1) with parameter η . Harmonic balance (HB) results (3.5,6), (3.3,4), (3.7)) are compared with the exact results obtained by numerically integrating the d.e. for the limit cycle (LC). The period is also compared with the Harmonic Balance result obtained by expanding to first order (FO) in η , equation (3.9), for $\eta < 1$. The last column shows the value of the second derivative when $x=0$, on the computed limit cycle.

Table 2

Harmonic Balance (HB) values of velocity amplitude B (4.3), displacement amplitude A (4.4), and period T (4.2), for the modified Malasoma nonlinear jerk equation (4.1), for several values of the parameters λ and γ , chosen such that $\lambda\gamma=3/4$ so, by (4.7), $B^{\text{HB}} = 1$, $A^{\text{HB}} = 1/\sqrt{\gamma}$, $T^{\text{HB}} = 2\pi/\sqrt{\gamma}$. These are compared with the exact limit cycle (LC) values, obtained by numerical integration of the d.e..

Figure 1. Jerk equation (4.1), $y = \dot{x}$: parameters $\gamma=4$, $\lambda=3/16$; $\dot{x}(0) = 0.5$.

Figure 2. Jerk equation (4.1), $y = \dot{x}$: $\gamma=4, \lambda=3/16$; $\dot{x}(0) = 1$.

Figure 3. Jerk equation (4.1), $y = \dot{x}$, $z = \ddot{x}$: parameters $\gamma=4$, $\lambda=3/16$; $\dot{x}(0) = 1$.

Figure 4. Jerk equation (4.1), $z = \ddot{x}$: parameters $\gamma=4$, $\lambda=3/16$; $\dot{x}(0) = 1$. (Transients up to $\sim 100T$ omitted.)

Table 1

Period T , velocity amplitude B , and displacement amplitude A , for the Mulholland equation (3.1) with parameter η . Harmonic balance (HB) results (3.5,6), (3.3,4), (3.7)) are compared with the exact results obtained by numerically integrating the d.e. for the limit cycle (LC). The period is also compared with the Harmonic Balance result obtained by expanding to first order (FO) in η , equation (3.9), for $\eta < 1$. The last column shows the value of the second derivative when $x=0$, on the computed limit cycle.

η	T			B		A		$ \ddot{x} _{x=0} _{LC}$
	HB	LC	HB,FO	HB	LC	HB	LC	
0.1	6.3358	6.3369	6.3355	0.8170	0.8176	0.8239	0.8259	0.0055
0.5	6.5534	6.5799	6.5450	0.8184	0.8223	0.8536	0.8671	0.030
1	6.8460	6.9473		0.8185	0.8291	0.8918	0.9260	0.064
2	7.5457	7.8427		0.8121	0.8471	0.9752	1.0506	0.155

Table 2

Harmonic Balance (HB) values of velocity amplitude B (4.3), displacement amplitude A (4.4), and period T (4.2), for the modified Malasoma nonlinear jerk equation (4.1), for several values of the parameters λ and γ , chosen such that $\lambda\gamma=3/4$ so, by (4.7), $B^{\text{HB}} = 1$, $A^{\text{HB}} = 1/\sqrt{\gamma}$, $T^{\text{HB}} = 2\pi/\sqrt{\gamma}$. These are compared with the exact limit cycle (LC) values, obtained by numerical integration of the d.e..

<u>B</u>		<u>A</u>		<u>T</u>		$ \ddot{x} _{x=0} _{\text{LC}}$
HB	LC	HB	LC	HB	LC	
$\gamma = 1$, $\lambda = 3/4$						
1	0.9701	1	0.9742	6.2832	6.2493	0.071
$\gamma = 4$, $\lambda = 3/16$						
1	0.99945	0.5	0.4998	3.14159	3.14127	0.021
$\gamma = 9$, $\lambda = 1/12$						
1	0.99995	0.3333	0.3333	2.09440	2.09438	0.009